



DATALOGIC - QUICK LINK 200

QL200

QL200 ID-NET + POWER T-CONNECTION

- Fast, easy connection for ID-NET™ networks
- Compact dimensions
- Extra connection for supply voltage




PRODUCT DESCRIPTION

Quick Link is a complete series for fast, easy cabling of an ID-NET™ network by means of standard cables. QL100/150/200 are slave modules designed for use with the master modules QL300/500 or CBX100/500. Quick Link 200 is a T-connector used in ID-NET™ networks for distributing signals but not supply voltage. An additional connection provides the reader with supply voltage. The supply voltage then passes with the signals to the next network unit. This allows larger networks to be created which would otherwise not be possible due to the total current limit and/or voltage drop.


TECHNICAL DATA

IP class	IP65
Power consumption max	4 A
Storage temperature max	70 °C
Storage temperature min	-20 °C
Supply voltage dc max	30 V DC
Supply voltage dc min	10 V DC
Temperature operational max	50 °C
Temperature operational min	0 °C
Weight	122 g


Reader 25P D-Sub Female	
Pin	Function
1, shell, both bushings	Reader Chassis
13	Vdc
25	GND
23	ID+
24	ID-
20	RXA
21	TXA





QL200 only (Ext. Power) M12 3P Male (B-coded)	
Pin	Function
1	Earth
2	Vdc
3	GND



ID-NET Out M12 5P Female (A-coded)	
Pin	Function
1	Shield
2	Vdc
3	GND
4	ID+
5	ID-




ID-NET In M12 5P Male (A-coded)	
Pin	Function
1	Shield
2	Vdc +
3	GND
4	ID+
5	ID-





QL200


Reader 25P D-Sub Female	
Pin	Function
1, shell, both bushings	Reader Chassis
13	Vdc
25	GND
23	ID+
24	ID-
20	RXA
21	TXA





QL200 only (Ext. Power) M12 3P Male (B-coded)	
Pin	Function
1	Earth
2	Vdc
3	GND



ID-NET Out M12 5P Female (A-coded)	
Pin	Function
1	Shield
2	Vdc
3	GND
4	ID+
5	ID-



ID-NET In M12 5P Male (A-coded)	
Pin	Function
1	Shield
2	Vdc +
3	GND
4	ID+
5	ID-

QL200